
2/16/24, 2:16 PM ct2230s_a.htm

source = "http://soundblaster.co.kr:80/modell/ct2230s.htm"



General

- FM Synthesis: Yes
- Wave Synthesis: Not Applicable
- Built-In Stereo Power Amplifier: Yes
- Built-In Digital/Analog Mixer: Yes
- Plug and Play: No
- CD-ROM Interface: Sony

Hardware Settings

Default settings are shown in [brackets]

- Interrupt (IRQ): 2, [5], 7, 10
- 8-bit DMA Channel: 0, [1], 3
- 16-bit DMA Channel: [5], 6, 7
- Joystick I/O Address: 200 Hex

Joystick: [Enabled] Disabled JYEN ON OFF

2/16/24, 2:16 PM ct2230s a.htm

• Audio I/O Address: [220], 240, 260, 280 Hex

```
ADDRESS: [220] 240 260 280 IOS0 ON OFF ON OFF IOS1 ON ON OFF OFF
```

• MPU-401 I/O Address: 300, [330] Hex

Port address: 300 [330] MSEL OFF ON

- MPU-401 [Enabled] (MPUEN closed), Disabled (MPUEN open)
- FM Synthesizer I/O Address: 388 Hex
- Wave Synthesizer I/O Address: Not Applicable
- CSP Chip Installed (enabled on CT2230S, disabled on CT2239S)

CSP Chip: Enabled Disabled IFSD, APSD OFF ON

Connectors

Line-In: YesMic-In: YesLine-Out: YesSpeaker-Out: YesPC Speaker-In: Yes

• Game/Joystick Port: Yes

• CD-ROM Audio-In (SB Audio Socket): Yes

• CD-ROM Audio-In (MPC2 Socket): No

• CSP Chip Socket: Yes (CSP chip built-in in CT2230S)

• Wave Blaster Daughter Board Connector: Yes

• External CD-ROM: Not Applicable

• Modem Feature Connector: Not Applicable